

DATA SHEET

Hall Effect Current Sensor



PN: CHB_BS3S1H

IPN=20~200A

Feature

- Closed- loop (compensated) current transducer
- Capable measurement of currents: DC, AC,pulse with galvanic isolation between primary circuit and secondary circuit.
- Supply voltage:DC +3.3V
- PCB mounting installation

Advantages

- High accuracy
- Low temperature drift
- Optimized response time, no insertion losses
- Low power consumption

Applications

- The application of variable frequency electrical appliances
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- Inverter applications



RoHS



Electrical data: (Ta=25°C, Vc=+3.3VDC,RL=2KΩ,CL=10000pF)

Parmeter \ Ref	CHB20BS3S1H	CHB50BS3S1H	CH100BS3S1H	CHB200BS3S1H
Rated input Ip(A)	20	50	100	200
Measuring range Ip(A)	0~±20	0~±50	0~±100	0~±200
Turns ratio Np/NS (T)	1:2000	1:2500	1:4000	1:4000
Inside resistance RM(Ω)	31.25±0.1%	15.6±0.1%	12.5±0.1%	6.25±0.1%
Output voltage Vo(V)	1.650±1.250*(IP/IPN)			
Output voltage Vo(V)	@IP=0,T=25°C		1.6500	
Reference voltage VR(V)	@Internal reference, reout		1.650	
Supply voltage VC(V)	+3.3 ±5%			
Accuracy XG(%)	@IPN,T=25°C		< ±0.5	
Offset voltage VOE(mV)	@IP=0,T=25°C		< ±10	
Temperature variation of VOE VOT(mV/°C)	@IP=0,-40 ~ +85°C		< ±0.05	
Linearity error εr(%FS)	< 0.1			
Di/dt accurately followed (A/μs)	> 50			
Response time tra(μs)	@90% of IPN		< 1.0	
Power consumption IC(mA)	10+Is			
Bandwidth BW(KHZ)	@-3dB,IPN		DC-200	

Insulation voltage Vd(KV)	@50/60Hz, 1min,AC	3.0
---------------------------	-------------------	-----

General data:

Parameter	Value
Operating temperature TA(°C)	-40 ~ +85
Storage temperature TS(°C)	-55~ +125
Mass M(g)	70
Plastic material	PBT G30/G15, UL94- V0;
Standards	IEC60950-1:2001
	EN50178:1998
	SJ20790-2000

Dimensions(mm):

	<p>Connection</p>
	<p>General tolerance</p> <p>General tolerance: <math>\pm 0.5\text{mm}</math> Primary through-hole: $10.5 \times 20.5 \pm 0.3$ Connection of Secondary : 2510-04A (Instead of Molex 5045-04A)</p>

Remarks:

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.
- The dynamic performance is the best when the primary hole is fully filled with.
- The primary conductor should be <math>< 100^{\circ}\text{C}</math>.

WARNING : Incorrect wiring may cause damage to the sensor.