

DATA SHEET

Hall Effect Current Sensor



PN: CHB_LTA24S2H

IPN=50~200A

Feature

- Closed- loop (compensated) current transducer
- Capable measurement of currents: DC, AC,pulse with galvanic isolation between primary circuit and secondary circuit.
- Supply voltage: DC +24.0V

Advantages

- High accuracy
- Low temperature drift
- Optimized response time, no insertion losses
- Low power consumption

Applications

- The application of variable frequency electrical appliances
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- Inverter applications



RoHS



Electrical data: (Ta=25°C, Vc=+24.0VDC,RL=2KΩ,CL=10000pF)

Ref Parmeter	CHB50LTA24S2H	CHB100LTA24S2H	CHB200 LTA24S2H
Rated input I _{pn} (A)	50	100	200
Measuring range I _p (A)	0 ~ ±50	0 ~ ±100	0 ~ ±200
Turns ratio N _p /N _S (T)	1:2000	1:4000	1:4000
Inside resistance R _M (Ω)	20±0.1%	20±0.1%	10±0.1%
Output voltage V _o (V)	2.500±2.0*(IP/IPN)		
Output voltage V _o (V)	@IP=0,T=25°C	2.500	
Reference voltage V _R (V)	@Internal reference,re out	2.500	
Supply voltage V _C (V)		+24.0±5%	
Accuracy X _G (%)	@IPN,T=25°C	< ±0.2	
Repeat accuracy X _{GR} (%)	@IPN,T=25°C	< ±0.2	
Offset voltage V _{OE} (mV)	@IP=0,T=25°C	< ±5.0	
Temperature variation of V _{OE} V _{OT} (mV/°C)	@IP=0,-40 ~ +85°C	< ±0.02	
Temperature variation of V _o V _{MT} (mV/°C)	@IP=0,-40 ~ +85°C	< ±0.05	

Linearity error $\epsilon_r(\%FS)$		< 0.1
Di/dt accurately followed (A/ μs)		> 50
Response time $\tau_r(\mu s)$	@90% of IPN	< 1.0
Power consumption $I_C(mA)$		10+Is
Bandwidth BW(KHZ)	@-3dB,IPN	DC-100
Insulation voltage $V_d(KV)$	@50/60Hz, 1min,AC	3.0

General data:

Parameter	Value
Operating temperature $T_A(^{\circ}C)$	-40 ~ +125
Storage temperature $T_S(^{\circ}C)$	-55~ +150
Mass $M(g)$	50
Plastic material	PBT G30/G15, UL94- V0;
Standards	IEC60950-1:2001
	EN50178:1998
	SJ20790-2000

Dimensions(mm):

	<p>Connection</p>
	<p>General tolerance</p>
	<p>General tolerance: <math>\pm 0.5mm</math> Primary through-hole: $D20 \pm 0.3mm$; Connection of Secondary : 2510-04A (Instead of Molex 5045-04A)</p>

Remarks:

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.
- The dynamic performance is the best when the primary hole is fully filled with.
- The primary conductor should be <math>< 100^{\circ}C</math>.

WARNING : Incorrect wiring may cause damage to the sensor.