

# DATA SHEET

## Hall Effect Current Sensor



**PN: CHK\_KS5S2**

**IPN=400-2000A**

### Feature

- Open- loop
- Capable measurement of currents: DC, AC,pulse with galvanic isolation between primary circuit and secondary circuit.
- Supply voltage: DC +5.0V

### Advantages

- Easy installation
- No insertion losses
- Low power consumption
- Wide current measuring range
- High immunity to external interference

### Applications

- Inverter applications
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- Frequency drive control home appliances



RoHS



### Electrical data: (Ta=25°C, Vc=+5.0VDC,RL=2KΩ)

| Parameter   | Ref               | CHK400<br>KS5S2    | CHK600<br>KS5S2 | CHK800<br>KS5S2 | CHK1000<br>KS5S2 | CHK1200<br>KS5S2 | CHK2000<br>KS5S2 |
|---|-------------------|--------------------|-----------------|-----------------|------------------|------------------|------------------|
| Rated input I <sub>pn</sub> (A)                                     |                   | 400                | 600             | 800             | 1000             | 1200             | 2000             |
| Measuring range I <sub>p</sub> (A)                                  |                   | 0~±400             | 0~±600          | 0~±800          | 0~±1000          | 0~±1200          | 0~±2000          |
| Output voltage V <sub>o</sub> (V)                                   |                   | 2.500±2.0*(IP/IPN) |                 |                 |                  |                  |                  |
| Output voltage V <sub>o</sub> (V)                                   | @IP=0,T=25°C      | 2.500              |                 |                 |                  |                  |                  |
| Load resistance R <sub>L</sub> (KΩ)                                 |                   | >2.0               |                 |                 |                  |                  |                  |
| Supply voltage V <sub>C</sub> (V)                                   |                   | +5.0 ±5%           |                 |                 |                  |                  |                  |
| Accuracy X <sub>G</sub> (%)   | @IPN,T=25°C       | < ±1.0             |                 |                 |                  |                  |                  |
| Offset voltage V <sub>OE</sub> (mV)                                 | @IP=0,T=25°C      | < ±25              |                 |                 |                  |                  |                  |
| Temperature variation of V <sub>OE</sub><br>V <sub>OT</sub> (mV/°C) | @IP=0,-40 ~ +85°C | < ±1.0             |                 |                 |                  |                  |                  |
| Hysteresis offset voltage<br>V <sub>OH</sub> (mV)                   | @IP=0,after 1*IPN | < ±20              |                 |                 |                  |                  |                  |
| Linearity error ε <sub>r</sub> (%FS)                                |                   | < 1.0              |                 |                 |                  |                  |                  |
| Di/dt (A/μs)  |                   | > 100              |                 |                 |                  |                  |                  |
| Response time τ <sub>ra</sub> (μs)                                  | @90% of IPN       | < 5.0              |                 |                 |                  |                  |                  |
| Power consumption I <sub>C</sub> (mA)                               |                   | 15                 |                 |                 |                  |                  |                  |
| Bandwidth B <sub>w</sub> (KHZ)                                      | @-3dB, IPN        | DC-20              |                 |                 |                  |                  |                  |

|                           |                   |     |
|---------------------------|-------------------|-----|
| Insulation voltage Vd(KV) | @50/60Hz, 1min,AC | 6.0 |
|---------------------------|-------------------|-----|

## General data:

| Parameter                    | Value                  |
|------------------------------|------------------------|
| Operating temperature TA(°C) | -40 ~ +85              |
| Storage temperature TS(°C)   | -55~ +125              |
| Mass M(g)                    | 200                    |
| Plastic material             | PBT G30/G15, UL94- V0; |
| Standards                    | IEC60950-1:2001        |
|                              | EN50178:1998           |
|                              | SJ20790-2000           |

## Dimensions(mm):

|  |   |
|--|---|
|  | <p>Connection</p>   |
|  | <p>General tolerance</p> <p>General tolerance: &lt;math&gt;\pm 0.5\text{mm}&lt;/math&gt;<br/> Primary through-hole: <math>16.0 \times 64.0 \pm 0.3</math><br/> Connection of secondary :<br/> CHK-KS5S2M:<br/> 2510-04A (Instead of Molex 5045-04A)<br/> CHK-KS5S2S: 15EDGK3.81-04P</p> |

## Remarks:

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.
- The dynamic performance is the best when the primary hole is fully filled with.
- The primary conductor should be <math>< 100^\circ\text{C}</math>.

**WARNING : Incorrect wiring may cause damage to the sensor.**