

DATA SHEET

Hall Effect Current Sensor



PN: CHK_LSP5S2L

IPN=15-50A

Feature

- Open-loop
- Capable measurement of currents: DC, AC, pulse with galvanic isolation between primary circuit and secondary circuit.
- Supply voltage: DC +5.0V

Advantages

- High accuracy
- Easy installation
- Low temperature drift
- Low power consumption
- Optimized response time, no insertion losses
- High immunity to external interference
- Very good linearity
- Can be customized

Applications

- Photovoltaic (PV) current applications
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- Inverter applications



RoHS



Electrical data: ($T_a=25\pm 5^\circ\text{C}$, $V_c=+5.0\text{VDC}$, $R_L=2\text{K}\Omega$)

Parameter \ Ref	CHK15 LSP5S2L	CHK20 LSP5S2L	CHK25 LSP5S2L	CHK30 LSP5S2L	CHK50 LSP5S2L	CHK60 LSP5S2L
Rated input I_{pn} (A)	15	20	25	30	50	60
Measuring range I_p (A)	0 ~ ± 15	0 ~ ± 20	0 ~ ± 25	0 ~ ± 30	0 ~ ± 50	0 ~ ± 60
Output voltage V_o (V)	2.500 \pm 2.000* (I_p/I_{pn})					
Output voltage V_o (V)	@ $I_p=0, T=25^\circ\text{C}$ 2.500					
Supply voltage V_c (V)	+5.0 \pm 5%					
Accuracy X_G (%)	@ $I_{pn}, T=25^\circ\text{C}$ < ± 1.0					
	@ $I_p=I_{pn}, -40 \sim +85^\circ\text{C}$ < ± 1.5					
Offset voltage V_{OE} (mV)	@ $I_p=0, T=25^\circ\text{C}$ < ± 20					
Temperature variation of V_{OE} V_{OT} (mV/ $^\circ\text{C}$)	@ $I_p=0, -40 \sim +85^\circ\text{C}$ < ± 0.1					
Linearity error ϵ_r (%FS)	< 1.0					
Di/dt accurately followed (A/ μs)	> 50					
Response time t_{ra} (μs)	@90% of I_{pn} < 3.0					
Power consumption I_c (mA)	< 12					

Bandwidth Bw(KHZ)	@-3dB, Ipn	DC-50
Insulation voltage Vd(KV)	@50/60Hz, 1min,AC	4.0
Immunity of EFT pulse train V _{EFT}	@±2KV, 5/50ns, 5KHZ/100KHZ,	A Class

General data:

Parameter	Value
Operating temperature TA(°C)	-40 ~ +85
Storage temperature TS(°C)	-55 ~ +125
Mass M(g)	10
Plastic material	PBT G30/G15, UL94- V0;
Standards	IEC60950-1:2001
	EN50178:1998
	SJ20790-2000

Dimensions(mm):

	Connection
	<p>For better EMC protection, we suggest: $RL > 4.7K \Omega$, $CL < 4.7nF$</p>
	General tolerance
	General tolerance: $< \pm 0.2mm$ Primary through-hole: $D 8.5 \pm 0.15mm$ Fixed pin: $0.8 * 0.9 \pm 0.15mm$; Secondary pin: 3pin $0.25 * 0.5$

Remarks:

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.
- The dynamic performance is the best when the primary hole is fully filled with.
- The primary conductor should be $< 100^\circ C$.

WARNING : Incorrect wiring may cause damage to the sensor.