

DATA SHEET

Hall Effect Current Sensor



PN: CHB_LE15D50

IPN=100A

Feature

- Closed- loop (compensated) current transducer
- Capable measurement of currents: DC, AC,pulse with galvanic isolation between primary circuit and secondary circuit.
- Supply voltage: DC $\pm 12\sim 15$ V

Advantages

- High accuracy
- Easy installation
- Low temperature drift
- Optimized response time
- High immunity to external interference

Applications

- The application of induction cooker
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- Inverter applications



RoHS



Electrical data: ($T_a=25^\circ\text{C}$, $V_c= \pm 15\text{VDC}$)

Parameter	Ref	CHB100 LE15D50
Rated input $I_{pn}(A)$		100
Measuring range $I_p(A)$		0 ~ 100
Turns ratio $N_p/N_S (T)$		1:2000
Output current rms $I_S(mA)$		$\pm 50 * I_P / I_{PN}$
Secondary coil resistance $R_S (\Omega)$		40
Inside resistance $R_M (\Omega)$		$[(V_C - 3.0V) / (I_S * 0.001)] - R_S$
Supply voltage $V_C(V)$		$(\pm 12 \sim \pm 15) \pm 5\%$
Accuracy $X_G(\%)$	@ $I_{PN}, T=25^\circ\text{C}$	$< \pm 0.5$
Offset current $I_{OE}(mA)$	@ $I_P=0, T=25^\circ\text{C}$	$< \pm 0.2$
Temperature variation of IOE $I_{OT}(mA/^\circ\text{C})$	@ $I_P=0, -40 \sim +85^\circ\text{C}$	$< \pm 0.005$
Linearity error $\epsilon_r(\%FS)$		< 0.1
Di/dt accurately followed ($A/\mu s$)		> 100
Response time $t_{ra}(\mu s)$	@90% of I_{PN}	< 1.0
Power consumption $I_C(mA)$		15+ I_S

Bandwidth BW(KHZ)	@-3dB,IPN	DC-200
Insulation voltage Vd(KV)	@50/60Hz, 1min,AC	3.0

General data:

Parameter	Value
Operating temperature TA(°C)	-40 ~ +85
Storage temperature TS(°C)	-55~ +125
Mass M(g)	40
Plastic material	PBT G30/G15, UL94- V0;
Standards	IEC60950-1:2001
	EN50178:1998
	SJ20790-2000

Dimensions(mm):

	Connection
	General tolerance
General tolerance: $\pm 0.5\text{mm}$ Primary through-hole: $D15 \pm 0.15\text{mm}$ Secondary pin: 3pin 0.6*0.65	

Remarks:

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.
- The dynamic performance is the best when the primary hole is fully filled with.
- The primary conductor should be <math>< 100^{\circ}\text{C}</math>.

WARNING : Incorrect wiring may cause damage to the sensor.